

BCN-P5999-0999-F(2007)MEE

リアルタイムデータアナライザインストール手順書

ご使用の前にお読みください

ご使用になる前に、本資料をお読みください。お読みになった後は、いつでも使用できるように大切に保管してください。また、本製品のユーザが代わる場合も、必ず最終ユーザのお手元へ届くようお願いいたします。使用時の注意事項については、下記を参照してください。

マニュアル名称	マニュアル番号
リアルタイムデータアナライザユーザーズマニュアル	SH-081870

▲本書に関するご注意

- 本書の内容の一部または全部を当社に断りなく、いかなる形で転載または複製することは、固くお断りします。
- 本書の記述内容はソフトウェア、ハードウェアの改訂に追従するように努力しておりますが、やむなく同期できない場合も生じます。
- 本書に記載されている内容はお断りなしに変更することがありますのでご了承ください。

1. 動作環境

項目	内容
パソコン本体	PC/AT互換機
CPU	Intel® Core-i3 2コア以上 64ビット対応アーキテクチャー
必要メモリ	8GB以上
ハードディスク空き容量	32GB以上
ディスプレイ	WXGA(1280×800ドット)以上
OS ^{*1}	Windows® 10 (Pro, Enterprise, IoT Enterprise)
(日本語版、英語版、中国簡体字版)	
通信用インタフェース	Ethernetポート

*1 64ビット版のみ対応します。

- 下記の機能を使用した場合、本製品は正常に動作しない可能性があります。
 - Windows互換モードでのアプリケーション起動
 - ユーザ簡易切替え
 - Windowsタッチまたはタッチ
 - クライアントHyper-V
 - 仮想デスクトップ
 - タブレットモード
 - Windowsの休止およびスリープ(スタンバイ)
 - 統合書き込みフィルター
- 下記の場合、本製品の画面が正常に動作しない可能性があります。
 - Windowsの設定で、“テキスト、アプリ、その他の項目のサイズを変更する”を100%以外に設定した場合
 - 詳細は、下記を参照してください。
 - 「」リアルタイムデータアナライザユーザーズマニュアル[SH-081870]
 - 動作中に画面の解像度を変更した場合
 - マルチディスプレイに設定した場合
- 「標準ユーザ」、「管理者」で使用してください。
- リモートデスクトップを行った場合、下記の現象が発生する可能性があります。
 - ネットワーク環境(速度や負荷など)に起因する、モニタまたは操作時などに表示される画面の更新遅れ
 - リモートデスクトップの画面設定に起因する、文字切れやウィンドウ切れなど

2. インストール手順

2.1 インストール前に確認してください。

- パソコンへは、「管理者」または「Administrator」のユーザとしてログインしてください。
- インストールを行う前に、動作させているすべてのアプリケーションを終了させてください。他のアプリケーションが動作している状態でインストールすると、製品が正常に動作しない場合があります。
- システムドライブの空き容量を1GB以上確保してください。
- インストーラフォルダのパスが半角英数のみで構成されるようにしてください。
- .NET Framework 3.5が無効になっている場合、有効にする必要があります。
- 統合書き込みフィルターを無効にしてください。

2.2 手順

- リアルタイムデータアナライザのインストーラフォルダ^{*1}*2*3の“setup.exe”をダブルクリックしてください。
- 画面の指示に従って必要事項を選択または入力します。^{*4}*5*6*7
- ネットワークドライブに配置した場合、インストール後のリアルタイムデータアナライザが正常に動作しない可能性があります。
- フォルダ名が半角スペースで始まっているフォルダが存在するディレクトリに配置した場合、正常にインストールを実行できなくなります。
- インストーラフォルダ名に、ASCII文字以外の文字を使用しないでください。リアルタイムデータアナライザのインストールに失敗する可能性があります。
- インストール先のフォルダ名には、フォルダ名に指定できない文字列(「”」のみや「\」のみなど)を指定しないでください。
- リアルタイムデータアナライザをインストールすると、ライセンス管理ユーティリティおよびGX LogViewerも同時にインストールされます。GX LogViewerのインストール完了後にコンピュータの再起動に関するメッセージが表示された場合、必ずその後コンピュータを再起動するようにしてください。
- インストール中に、Windowsアップデートなどのコンピュータの再起動を確認するメッセージが表示された場合でも、コンピュータを再起動しないでください。
- 上書きインストールを行う際の表示言語は、前回インストールを行った際の表示言語と同じです。

3. 製品構成

形名	品名	個数
SW1DND-RDA-MQ12	リアルタイムデータアナライザ	1
SW1DND-RDA-MQ06	製品DVD-ROM	1
SW1DND-RDA-MQ03	インストール手順書(本書)	1
	ソフトウェア使用契約書	1
	ライセンス申込手順書	1
	エンタイトルメントID通知書	1

4. アンインストール手順

Windowsのコントロールパネルからアンインストールしてください。^{*1}

*1 ライセンス管理ユーティリティおよびGX LogViewerはアンインストールされません。

MicrosoftおよびWindowsは、米国Microsoft Corporationの米国およびその他の国における登録商標または商標です。Intelは、米国およびその他の国におけるIntel Corporationの登録商標または商標です。本文中における会社名、システム名、製品名などは、一般に各社の登録商標または商標です。本文中で、商標記号(™, ®)は明記していない場合があります。

Real-time Data Analyzer Installation Instructions

Before Using the Product

Please read this document before use. Keep the document in a safe place for future reference. Make sure that the end users read the document.

For the precautions on using Real-time Data Analyzer, refer to the following manual.

Manual name	Manual number
Real-time Data Analyzer User’s Manual	SH-081873ENG

▲Notice

- Reprinting or reproducing the part or all of the contents of this document in any form for any purpose without the permission of Mitsubishi Electric Corporation is strictly forbidden.
- Although we have made the utmost effort to follow the revisions of the software and hardware, in some cases, unsynchronized matter may occur.
- The information in this document may be subject to change without notice.

1. Operating Environment

Items	Contents
Personal computer	PC/AT compatible personal computer
CPU	Intel® Core-i3 2 cores or more 64-bit architecture
Required memory	8 GB or more
Available hard disk capacity	32 GB or more
Monitor	WXGA(1280×800 dots) or more
OS ^{*1}	Windows® 10 (Pro, Enterprise, IoT Enterprise)
(English version, Japanese version, or Simplified Chinese version)	
Communication interface	Ethernet port

*1 64-bit version only

- When the following functions are used, this product may not run properly.
 - Application start-up in Windows compatibility mode
 - Fast user switching
 - Windows Touch or Touch
 - Client Hyper-V
 - Virtual desktop
 - Tablet mode
 - Windows hibernate or sleep (standby)
 - Unified Write Filter
- In the following cases, the screen of this product may not work properly.
 - A value other than 100% is set for “Change the size of text, apps, and other items” in Windows.
 - For details, refer to the following manual.
 - 「」Real-time Data Analyzer User’s Manual [SH-081873ENG]
 - The resolution of the screen is changed in operation.
 - The multi-display is set.
- Use this product with the authority of a ‘Standard user’ or ‘Administrator’.
- When the remote desktop function is used, the following issues may occur.
 - Screen update delay displayed during a monitoring or an operation due to network environment (speed, load, and so on)
 - Truncation of texts or windows due to the screen setting of a remote desktop.

2. Installation

2.1 Confirm before installation.

- Log on to the personal computer as an administrator.
- Close all running applications before installation. If the product is installed while other applications are running, it may not operate normally.
- Secure at least 1 GB free space on the system drive.
- Make sure that the path of the installation folder consists only of single-byte alphanumeric characters.
- Enable .NET Framework 3.5 if it is disabled.
- Disable Unified Write Filter.

2.2 Procedure

- Double-click “setup.exe” in the installer folder^{*1}*2*3 of Real-time Data Analyzer.
- Select or enter the necessary information by following the on-screen instructions.^{*4}*5*6*7
- If it is stored in the network drive, the installed Real-time Data Analyzer may not work properly.
- If it is stored to a folder where a folder whose name begins with a space is included, the installation cannot be performed normally.
- Do not use non-ASCII characters for the folder name of an installation destination. Otherwise, the installation of Real-time Data Analyzer will fail.
- Do not specify a character not available as a folder name of an installation destination (using “”” or “\” only for example).
- When Real-time Data Analyzer is installed, License Manager and GX LogViewer will also be installed. Be sure to restart the computer later when a message related to the restart of the computer appears after installing GX LogViewer.
- Do not restart the computer even if a message checking whether restart the computer or not appears such as Windows update during installation.
- The language displayed when installing this product with overwriting the existing one is the same as the one displayed in the previous installation.

3. Packing List

Model name	Product name	Quantity
SW1DND-RDA-MQ12	Real-time Data Analyzer	1
SW1DND-RDA-MQ06	DVD-ROM	
SW1DND-RDA-MQ03	Installation Instructions (This document)	1
	End-user software license agreement	1
	License Application Instructions	1
	Entitlement ID Notification	1

4. Uninstallation

Uninstall Real-time Data Analyzer from the control panel of Windows.^{*1}

*1 License Manager and GX LogViewer are not uninstalled.

Microsoft and Windows are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. Intel is either a registered trademark or a trademark of Intel Corporation in the United States and/or other countries.

The company names, system names and product names mentioned in this manual are either registered trademarks or trademarks of their respective companies. In some cases, trademark symbols such as ™ or ® are not specified in this manual.